

Solving the Schwinger-Dyson Equations for Gluodynamics in the Maximal Abelian Gauge*

T. Shinohara^{a†}, K.-I. Kondo^{ab} and T. Murakami^a

^aGraduate School of Science and Technology, Chiba University, Chiba 263-8522, Japan

^bDepartment of Physics, Faculty of Science, Chiba University, Chiba 263-8522, Japan

We derive the Schwinger-Dyson equations for the $SU(2)$ Yang-Mills theory in the maximal Abelian gauge and solve them in the infrared asymptotic region. We find that the infrared asymptotic solutions for the gluon and ghost propagators are consistent with the hypothesis of Abelian dominance.

1. Introduction

The Schwinger-Dyson (SD) equation is one of the most popular approaches to investigate the non-perturbative features of quantum field theory. The analyses by making use of the SD equation for quark propagator are well-known. Recently, the coupled SD equations for the gluon and ghost propagators in Yang-Mills theory have been studied mainly in the Lorentz (Landau) gauge.[1,2] In this paper, we derive the SD equations for the $SU(2)$ Yang-Mills theory in the maximal Abelian (MA) gauge and solve them analytically in the infrared (IR) asymptotic region. The MA gauge is useful to investigate the Yang-Mills theory from the view point of the dual superconductivity.

In the MA gauge, in contrast to the ordinary Lorentz gauge, we must explicitly distinguish the diagonal components of the fields from the off-diagonal components. This is indeed the case even in the perturbative analysis in the UV region.[3] Therefore, we must take account of the four propagators for the diagonal gluon, off-diagonal gluon, diagonal ghost and off-diagonal ghost. Numerical behaviors of gluon propagators in the MA gauge are also investigated on a lattice simulation.[4]

2. SD equations in the MA gauge

First, we derive the SD equations from the $SU(2)$ Yang-Mills action in the MA gauge[3]. The graphical representation of SD equations are shown in Figure 1. For the diagonal gluon propagator, we adopt the Landau gauge so that the diagonal gluon propagator $D_{\mu\nu}(p^2)$ has only the transverse part

$$D_{\mu\nu}(p^2) := \frac{F_d(p^2)}{p^2} P_{\mu\nu}^T, \quad (1)$$

where we defined the form factor $F_d(p^2)$. While, the off-diagonal gluon propagator $D_{\mu\nu}^{ab}(p^2)$ has both the transverse and longitudinal parts

$$D_{\mu\nu}^{ab} := \left[\frac{F_T(p^2)}{p^2} P_{\mu\nu}^T + \alpha \frac{F_L(p^2)}{p^2} P_{\mu\nu}^L \right] \delta^{ab}, \quad (2)$$

where we defined the form factors $F_T(p^2)$ and $F_L(p^2)$. The form factor $G(p^2)$ for the off-diagonal ghost propagator $\Delta^{ab}(p^2)$ is defined

$$\Delta^{ab}(p^2) := \frac{G(p^2)}{p^2} \delta^{ab}. \quad (3)$$

The diagonal ghost propagator is decoupled from the other fields so that we omit it hereafter.

Now, we write down the SD equations:

$$\begin{aligned} D_{\mu\nu}(q^2)^{-1} &= Z_a D_{\mu\nu}^{(0)}(q^2)^{-1} \\ &+ Z_C^2 \int_p \Gamma_\mu^{(0)da}(r, p) \Delta^{ab}(p) \Gamma_\nu^{bc}(p, r) \Delta^{cd}(r) \\ &- \frac{Z_A^2}{2} \int_p \Gamma_{\mu\rho\xi}^{(0)da}(r, p) D_{\xi\eta}^{ab}(p^2) \Gamma_{\nu\sigma\eta}^{bc}(p, r) D_{\rho\sigma}^{cd}(p^2) \\ &+ (\text{tadpole contributions}), \end{aligned} \quad (4)$$

*Supported by Sumitomo Foundations, Grant-in-Aid for Scientific Research (B)13135203 from MEXT, and (C)14540243 from JSPS.

[†]Speaker at the conference.

Figure 1. The graphical representation of the SD equations.

$$\begin{aligned} \Delta^{ab}(q^2)^{-1} &= Z_C \Delta^{(0)ab}(q^2)^{-1} \\ &- Z_C^2 \int_p \Gamma_{\mu}^{(0)ac}(r, p) \Delta^{cd}(p) \Gamma_{\nu}^{db}(p, r) D_{\mu\nu}(r) \\ &+ (\text{tadpole contributions}), \end{aligned} \quad (5)$$

and

$$\begin{aligned} D_{\mu\nu}^{ab}(q^2)^{-1} &= Z_A D_{\mu\nu}^{(0)ab}(q^2)^{-1} \\ &- Z_A^2 \int_p \Gamma_{\rho\mu\xi}^{(0)ac}(r, p) D_{\xi\eta}^{cd}(p) \Gamma_{\sigma\nu\eta}^{db}(p, r) D_{\rho\sigma}(r) \\ &+ (\text{tadpole contributions}). \end{aligned} \quad (6)$$

Here the contributions from the two-loop graphs have been omitted. The full form of SD equations will be given in a separate paper[5]. $\Gamma_{\mu}^{ac}(p, q)$ is the full vertex function for the diagonal gluon, off-diagonal ghost and off-diagonal antighost interaction, while $\Gamma_{\mu\rho\sigma}^{ac}(p, q)$ is the full vertex function for an interaction of the diagonal gluon and two off-diagonal gluons, and the superscript “(0)” means a *bare* propagator or vertex function.

In the MA gauge, we obtain the Slavnov-Taylor (ST) identities

$$(p - q)^{\mu} \Gamma_{\mu}^{ab}(p, q) = \Delta^{ab}(p^2)^{-1} - \Delta^{ab}(q^2)^{-1}, \quad (7)$$

$$(p - q)^{\mu} \Gamma_{\mu\rho\sigma}^{ab}(p, q) = D_{\rho\sigma}^{ab}(p^2)^{-1} - D_{\rho\sigma}^{ab}(q^2)^{-1}. \quad (8)$$

3. Truncation and Approximations

In order to solve the SD equations analytically, we employ the following approximations.

- We neglect the two-loop contributions.

- Instead of the full vertex functions, we adopt modified vertex functions which are compatible with the ST identities. We adopt approximations for vertex functions as

$$\Gamma_{\mu}^{ab}(p, q) \sim \Gamma_{\mu}^{(0)ab}(p, q) \partial_{p^2} \{p^2 G^{-1}(p^2)\}, \quad (9)$$

and

$$\Gamma_{\mu\rho\sigma}^{ab}(p, q) \sim \Gamma_{\mu\rho\sigma}^{(0)ab}(p, q) \partial_{p^2} \{p^2 F_T^{-1}(p^2)\}. \quad (10)$$

Here, we adopt the Feynman gauge for the off-diagonal gluon for simplicity, that is, $\alpha = 1$ and $F_T(p^2) = F_L(p^2)$. Substituting the bare form factors, which are $G(p^2) = F_T(p^2) = 1$, into the right hand side of the ansatz (9) and (10), we obtain the bare vertex functions. Moreover, these ansatz are compatible with the ST identities (7) and (8) in the limit of $p \rightarrow q$.

- In the momentum integration, we use the Higashijima-Miransky approximation[7] as

$$F((p - q)^2) = F(\max\{p^2, q^2\}). \quad (11)$$

4. Solving the SD equations

Now we adopt the ansatz for the form factors in the IR region:

$$\begin{aligned} F_d(p^2) &= A(p^2)^u + \dots, \\ G(p^2) &= B(p^2)^v + \dots, \\ F_T(p^2) &= C(p^2)^w + \dots. \end{aligned} \quad (12)$$

Substituting the ansatz (12) for the form factors, and the ansatz (9) and (10) for vertex func-

Table 1

The relation u , v and w (and v' , w') in the Feynman gauge ($\alpha = 1$).

	$w > 1$	$w = 1$
$v > 1$	$u = -\min\{v, w\}$	$u = -\min\{v, w'\}$
$v = 1$	$u = -\min\{v', w\}$	$u = -\min\{v', w'\}$

tions into the SD equations (4), (5) and (6), and comparing the leading term in the both sides of each equation, we obtain the following results for $\alpha = 1$.

1. From eqs. (5) and (6), we obtain the relations $v \geq 1$ and $w \geq 1$.
- 2a. In the case of $v > 1$ and $w > 1$, from the eq. (4), we obtain the relation $u = -\min\{v, w\}$ so that u is less than -1 .
- 2b. In the case of $v = 1$ and $w > 1$, we need redefine the form factor $G(p^2)$ as $G(p^2) = B_0 p^2 + B_1 (p^2)^{v'} + \dots$ with $v' > 1$ since contributions from the leading term of $G(p^2)$ are canceled each other in the ansatz (9). Therefore we need the information of next leading term of the form factor $G(p^2)$. In this case we obtain the relation $u = -\min\{v', w\}$ from the eq. (4) so that u is also less than -1 .
- 2c. Next, we consider the case of $v > 1$ and $w = 1$. As well as the above case, we need redefine the form factor $F_T(p^2)$ as $F_T(p^2) = C_0 p^2 + C_1 (p^2)^{w'} + \dots$ with $w' > 1$ and we obtain the relation $u = -\min\{v, w'\}$ ($u < -1$).
- 2d. Similarly, in the case of $v = w = 1$, we obtain the relation $u = -\min\{v', w'\}$ ($u < -1$).

The results are summarized in Table 1.

In the gauge other than the Feynman gauge, that is, $\alpha \neq 1$, the calculation and discussion are very tedious. However, the qualitative results are identical to the above case except for the following one point. In this case, even if $w = 1$, there occurs no cancellation as in the above two cases 2c and 2d. This is because the off-diagonal gluon propagator has the momentum dependent tensor structure for $\alpha \neq 1$, while it is proportional to $\delta_{\mu\nu}$ for $\alpha = 1$. Therefore, we obtain the relation $u = -1$ in the case of $w = 1$. (See Table 2.)

Table 2

The relation u , v and w (and v') in the gauge $\alpha \neq 1$.

	$w > 1$	$w = 1$
$v > 1$	$u = -\min\{v, w\}$	$u = -1$
$v = 1$	$u = -\min\{v', w\}$	$u = -1$

5. Conclusion

In the IR limit, the form factors of each propagator behave as

$$F_d(p^2) \sim A(p^2)^u + \dots \quad (u \leq -1), \quad (13)$$

$$G(p^2) \sim B(p^2)^v + \dots \quad (v \geq 1), \quad (14)$$

$$F_T(p^2) \sim C(p^2)^w + \dots \quad (w \geq 1). \quad (15)$$

Therefore the solution shows that the diagonal gluon propagator is enhanced in the IR limit, while the off-diagonal gluon and off-diagonal ghost propagators are suppressed in the IR region. Our results are compatible with a hypothesis of Abelian dominance[6].

REFERENCES

1. L. von Smekal, R. Alkofer and A. Hauck, Phys. Rev. Lett. 79,3591 (1997); L. von Smekal, R. Alkofer and A. Hauck, Ann. Phys. 267, 1 (1998).
2. D. Atkinson and J. C. Bloch, Phys. Rev. D 58, 094036 (1998).
3. T. Shinohara, T. Imai and K.-I. Kondo, hep-th/0105268, to be published in Intern. J. Mod. Phys. A.
4. V.G. Bornyakov, M.N. Chernodub, F.V. Gubarev, S.M. Morozov and M.I. Polikarpov, hep-lat/0302002.
5. K.-I. Kondo, T. Murakami and T. Shinohara, in preparation.
6. Z.F. Ezawa and A. Iwazaki, Phys. Rev. D 25, 2681-2689 (1982).
7. K. Higashijima, Phys. Rev. D29 (1984) 1228; V.A. Miransky, Nuovo Cimento A 90 (1985) 149.